

GOODWE

Cutting-edge hybrid inverter with smart operation modes and powerful back-up capabilities

- ✓ Lower energy cost
- ✓ Smart and flexible solutions
- ✓ Uninterrupted power supply
- ✓ Superb safety and performance

The ET G2 hybrid inverter is designed to maximise energy output, enhance self-consumption, and facilitate extensive back-up power for homeowners. With power rating up to 15kW, intelligent load controls and a wide battery voltage range, the inverter caters to individual needs. To secure a high level of energy autonomy, combine the hybrid inverter with GoodWe HV battery, and connect the system to the GoodWe EV chargers and/or any smart-grid ready household appliances. By combining a variety of smart operation modes, the system can be optimized to further drive down energy cost.



Smart operation modes



Powerful backup



Integrated smart meter

ET G2 Series

Hybrid Inverter | 6 – 15kW | Up to 3 MPPTs | Three Phase | HV

EMEA

Technical Data		GW6000-ET-20	GW8000-ET-20	GW10K-ET-20	GW12K-ET-20	GW15K-ET-20
Battery Input Data						
Battery Type ^{*1}		Li-Ion				
Nominal Battery Voltage (V)		500				
Battery Voltage Range (V)		150 ~ 720				
Start-up Voltage (V)		150				
Number of Battery Input		1				
Max. Continuous Charging Current (A)	30	30	40	40	40	
Max. Continuous Discharging Current (A)	30	30	40	40	40	
Max. Charging Power (W)	9000	12000	15000	18000	24000	
Max. Discharging Power (W)	6600	8800	11000	13200	16500	
PV String Input Data						
Max. Input Power (W) ^{*2}	9600	12800	16000	19200	24000	
Max. Input Voltage (V) ^{*3,4}		1000				
MPPT Operating Voltage Range (V) ^{*5}		120 ~ 850				
Start-up Voltage (V)		150				
Nominal Input Voltage (V)		620				
Max. Input Current per MPPT (A)		16				
Max. Short Circuit Current per MPPT (A)		24				
Number of MPP Trackers	2	2	3	3	3	
Number of Strings per MPPT		1				
AC Output Data (On-grid)						
Nominal Output Power (W)	6000	8000	10000	12000	15000	
Nominal Apparent Power Output to Utility Grid (VA)	6000	8000	10000	12000	15000	
Max. Apparent Power Output to Utility Grid (VA) ^{*6}	6000	8000	10000	12000	15000	
Max. Apparent Power from Utility Grid (VA)	12000	16000	20000	20000	20000	
Nominal Output Voltage (V)		400 / 380, 3L / N / PE				
Output Voltage Range (V) ^{*7}		170 ~ 290				
Nominal AC Grid Frequency (Hz)		50 / 60				
AC Grid Frequency Range (Hz)		45 ~ 65				
Max. AC Current Output to Utility Grid (A) ^{*8}	8.7	11.6	14.5	17.4	21.7	
Max. AC Current From Utility Grid (A)	15.7	21.0	26.1 ^{*9}	26.1 ^{*9}	26.1 ^{*9}	
Power Factor		0.8 leading~0.8 lagging				
Max. Total Harmonic Distortion		<3%				
AC Output Data (Back-up)						
Back-up Nominal Apparent Power (VA)	6000	8000	10000	12000	15000	
Max. Output Apparent Power without Grid (VA) ^{*10}	6000 (12000 @60sec)	8000 (16000 @60sec)	10000 (18000 @60sec)	12000 (18000 @60sec)	15000 (18000 @60sec)	
Max. Output Apparent Power with Grid (VA)	6000	8000	10000	12000	15000	
Max. Output Current (A)	13.0 (17.4 @60sec)	17.4 (23.3 @60sec)	21.7 (26.1 @60sec)	21.7 (26.1 @60sec)	21.7 (26.1 @60sec)	
Nominal Output Voltage (V)		400 / 380				
Nominal Output Frequency (Hz)		50 / 60				
Output THDv (@Linear Load)		<3%				
Efficiency						
Max. Efficiency	98.0%	98.0%	98.2%	98.2%	98.2%	
European Efficiency	97.2%	97.2%	97.5%	97.5%	97.5%	
Max. Battery to AC Efficiency	97.2%	97.5%	97.5%	97.5%	97.5%	
MPPT Efficiency		99.5%				
Protection						
PV Insulation Resistance Detection		Integrated				
PV AFCI3.0		Optional				
Residual Current Monitoring		Integrated				
PV Reverse Polarity Protection		Integrated				
Battery Reverse Polarity Protection		Integrated				
Anti-islanding Protection		Integrated				
AC Overcurrent Protection		Integrated				
AC Short Circuit Protection		Integrated				
AC Overvoltage Protection		Integrated				
DC Switch		Integrated				
DC Surge Protection		Type II				
AC Surge Protection		Type II				
Remote Shutdown		Integrated				
General Data						
Operating Temperature Range (°C)		-35 ~ +60				
Relative Humidity		0 ~ 100%				
Max. Operating Altitude (m)		4000				
Cooling Method		Natural Convection				
User Interface		LED, WLAN + APP				
Communication with BMS		RS485, CAN				
Communication with Meter		RS485				
Communication with Portal		WiFi + LAN + Bluetooth				
Weight (kg)	23	23	25	25	25	
Dimension (W x H x D mm)		496 x 460 x 221				
Topology		Non-isolated				
Ingress Protection Rating		IP66				
Mounting Method		Wall Mounted				

*1: The Li-Ion battery usually contain two mainstream type: LFP and Ternary Lithium battery.

*2: Max. input power, not continuous for 1.6*normal power. Besides, in Australia, for most of the PV modules, the max. input power can reach 2*Pn, for example, the max. input power of GW6000-ET-20 can reach 12000W.

*3: For 1000V system, the maximum operating voltage is 950V.

*4: When the input voltage ranges from 975V to 1000V, the inverter will enter the standby mode, and the voltage returns to 975V to enter the normal operation state.

*5: Please refer to the user manual for the MPPT Voltage Range at Nominal Power.

*6: According to the local grid regulation.

*7: Output Voltage Range: phase voltage.

*8: When the three-unbalance function is activated, the Max. AC Current Output to the on-grid load can reach 13A, 17.4A, 21.7A, 21.7A and 21.7A respectively.

*9: If the inverter is installed with the 3x25A AC breaker, it is suggested that the consumption and feed-in AC power should be less than 11040W (0.8x0.8x25x230x3), and this limitation can be set by SolarGo App.

*10: Can be reached only if PV and battery power is enough.

*: Please visit GoodWe website for the latest certificates.